

RF Bay, Inc. 2018 Short Form Catalog



Table of Contents

Low Noise Amplifier	2
LNA Series.....	2
ENA/GNA Series	6
WNA/BNA Series.....	8
ODA Series	8
Low Power Amplifier.....	9
LPA Series	9
EPA Series	10
GPA/LRA Series	11
DCA Series.....	12
Medium Power Amplifier	13
MGA Series	13
MPA Series.....	14
MRA Series.....	15
High Power Amplifier	15
HPA/SPA Series	15
Frequency Divider Prescaler.....	16
FBS/ FAS/FCS/FDS/FPS Series	16
Frequency Doubler.....	19
FDR/QDR Series.....	19
Frequency Tripler/Multiplier.....	20
FMR/FTR/FVR Series	20
Frequency Mixer	21
MXR Series.....	21
GXR Series.....	22
Power Splitter/Combiner	23
PSC Series	23
Directional Coupler	24
DCR Series.....	24
Phase Detector with Loop Filter	24
PDF Series	24
Temperature Compensated Crystal Oscillator.....	24
TCXO Series.....	24
Phase Locked Oscillator.....	24
PLO Series	24
Voltage Controlled Oscillator	25
VCO Series	25
Block Down Converter.....	26
BDC Series.....	26
Bandpass Filter.....	26
BPF Series	26
RF Power Detector	27
RPD Series.....	27
RF Switch.....	27
RFS Series.....	27

Low Noise Amplifier LNA Series

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
LNA-150	0.005 - 300	2.0	30	±0.5	+10	+23	1.3/1.5	12	40
LNA-200	200 - 300	1.1	21	±0.1	+19	+33	1.3/1.7	15	75
LNA-250	10 - 250	1.4	17	±0.5	+21	+39	1.4/1.1	5	160
LNA-300	225 - 400	0.8	21	±0.15	+17	+35	1.2/1.4	12	75
LNA-350	200 - 500	0.6	24	±1.7	+21	+35	2.2/1.6	5	80
LNA-400	150 - 600	0.8	21	±0.5	+17	+35	1.2/1.4	12	75
LNA-440	420 - 450	2.7	24	±0.25	+14	+26	2.5/1.2	12	15
LNA-450	50 - 450	1.4	34	±0.1	+18.5	+34	1.4/1.2	12	100
LNA-500	10 - 500	2.9	18	±1.8	+5	+14.5	1.5/1.7	12	16
LNA-500H	10 - 500	3.6	11	±1.2	+17.5	+30	1.5/1.7	12	60
LNA-510	10 - 550	1.7	27	±0.3	+19	+34	1.5/1.5	12	105
LNA-520	20 - 520	1.4	33	±0.3	+18	+34	1.4/1.2	12	100
LNA-530	1 - 500	2.0	30	±1.5	+13	+24	1.5/1.5	15	75
LNA-545	0.01 - 500	2.0	45	±0.5	+10	+20	1.4/1.3	15	75
LNA-547	10 - 700	2.0	47	±1.0	+22	+38	1.6/1.3	15	150
LNA-550	10 - 550	0.9	19	±0.5	+8	+20	1.5/1.2	12	30
LNA-580	10 - 580	0.7	23	±1.1	+19	+33	1.5/1.5	5	70
LNA-580T	10 - 580	0.7	23	±1.1	+19	+33	1.5/1.5	12	70
LNA-600	200 - 1000	0.85	20	±1.2	+17	+35	1.3/1.5	12	75
LNA-605	10 - 600	1.0	40	±0.8	+17	+31	1.5/1.2	5	135
LNA-650	0.03 - 600	2.2	50	±1.2	+14	+24	1.5/1.2	15	85
LNA-700	10 - 700	1.0	40	±2.5	+25	+35.8	1.5/1.2	5	240
LNA-725	5 - 700	1.5	25	±0.25	+23	+38	1.2/1.4	12	150
LNA-730	50 - 750	1.3	20	±1.5	+19	+33	1.3/1.2	12	75
LNA-750	300 - 1200	0.6	40	±4.0	+19	+34	1.4/1.4	12	125

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
LNA-800	300 - 1300	0.5	34	±5.0	+22.5	+39	1.9/1.4	12	190
LNA-840	10 - 800	2.0	40	±0.7	+17	+30	1.7/1.2	12	100
LNA-850	750 - 950	1.2	17	±0.75	+16.5	+30	1.4/1.2	5	60
LNA-900	880 - 960	1.2	23	±0.7	+13	+25	2.4/1.4	12	25
LNA-910	900 - 1000	0.7	10	±0.35	+13	+27	1.5/1.15	9 - 24	76
LNA-915	902 - 928	1.2	24	±0.1	+13	+25	2.4/1.4	12	25
LNA-925	350 - 1500	1.0	30	±0.85	+22	+33	1.8/1.4	5	160
LNA-930	30 - 930	1.3	30	±0.5	+19	+35	1.1/1.2	12	115
LNA-950	350 - 1550	0.5	34	±5.5	+18.5	+32	1.6/1.6	12	170
LNA-1000	10 - 1000	2.0	33	±1.2	+12	+23	1.6/1.5	12	40
LNA-1018	50 - 1000	1.0	18	±0.5	+16	+32	1.8/1.4	12	70
LNA-1024	100 - 1000	2.0	24	±0.25	+24	+40	1.5/1.5	12	160
LNA-1030	20 - 1000	1.3	30	±0.5	+18	+32	1.2/1.2	12	140
LNA-1035	500 - 1000	1.8	35	±0.3	+13	+24	1.5/1.4	12	80
LNA-1036	50 - 1000	1.0	36	±1.0	+22	+38	1.6/1.6	12	175
LNA-1045	50 - 1000	2.1	45	±0.35	+22	+32	1.8/1.5	12	140
LNA-1050	10 - 1000	2.2	50	±0.8	+13	+22	2.5/1.5	12	88
LNA-1070	30 - 1030	2.0	45	±1.2	+25	+37	1.9/1.5	12	195
LNA-1100	700 - 1500	0.6	37	±3.5	+19	+33	1.2/1.7	12	140
LNA-1150	300 - 2000	0.6	37	±7.5	+20	+33	1.5/1.8	12	150
LNA-1200	1150 - 1300	1.2	20	±1.2	+12	+24	2.0/1.6	12	25
LNA-1217	1200 - 1700	0.6	15	±1.3	+19	+34	1.4/1.8	12	45
LNA-1225	1215 - 1240	1.2	21	±0.1	+12	+24	1.7/1.9	12	25
LNA-1240	100- 1200	3.5	41	±0.5	+19	+32	1.5/1.5	15	150
LNA-1245	50- 1200	2.2	45	±1.0	+13	+23	1.2/1.2	12	88
LNA-1300	550- 1300	0.55	15.5	±3.5	+21	+38	1.1/1.5	5	90

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
LNA-1330	10- 1300	1.5	33	±0.5	+20	+34	1.3/1.3	12	165
LNA-1350	700- 2000	0.8	35	±5.5	+23	+37	1.6/1.2	12	170
LNA-1400	100- 1400	0.8	20	±2.2	+17	+35	1.25/1.35	12	75
LNA-1440	0.01- 1400	2.7	40	±1.0	+19	+32	1.4/1.5	15	120
LNA-1450	0.01- 1400	2.0	30	±3.9	+9	+21	1.5/1.8	12	35
LNA-1500	10- 1500	3.3	36	±1.8	+10	+23	1.5/2.0	12	45
LNA-1520	20- 1500	1.0	20	±1.2	+17	+35	1.5/1.5	12	70
LNA-1535	1000- 2000	1.0	35	±4.0	+23	+37	1.7/1.3	12	180
LNA-1550	50- 1550	2.7	47	±0.5	+20	+33	2.5/2.5	12	140
LNA-1560	750- 1750	1.1	35	±1.2	+19	+36	1.5/1.2	12	145
LNA-1570	50- 2000	3.2	40	±1.75	+24	+37	1.4/1.5	12	200
LNA-1620	1600- 2000	1.1	18	±1.1	+14	+25	1.9/1.3	12	25
LNA-1700	1400- 2000	1.4	16.5	±1.25	+16	+29	1.2/1.7	5	50
LNA-1800	0.001- 1800	2.2	30	±6.0	+8	+20	1.9/1.4	12	40
LNA-1820	1800- 2000	1.1	16	±0.25	+26	+39	1.7/1.4	5	160
LNA-1822	1800- 2200	1.3	17.5	±0.9	+14	+25	1.7/1.4	12	25
LNA-1835	200- 1800	1.8	35	±0.3	+13	+24	2.0/1.4	12	35
LNA-2000	0.01- 2000	3.2	26	±2.0	+10	+23	1.5/1.4	12	45
LNA-2024	2000- 2400	1.4	17	±0.4	+13	+25	1.7/1.4	12	25
LNA-2030	2000- 3000	0.9	19	±2.7	+19.5	+33.5	1.7/2.0	5	95
LNA-2227	2200- 2700	1.4	16	±0.7	+14	+26	1.6/1.3	12	25
LNA-2250	1650- 2250	0.8	18	±2.1	+20	+36	1.4/1.3	5	115
LNA-2400	2400- 2500	1.8	20	±0.3	+9	+18	2.0/1.3	12	45
LNA-2425	2400- 2500	0.85	14	±0.1	+26	+39	1.9/1.2	5	170
LNA-2428	2400- 2800	1.6	15	±0.65	+13	+25	1.6/1.3	12	25
LNA-2450	2400- 2500	1.5	16	±0.25	+14	+26	1.6/1.3	12	25

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
LNA-2500	0.1- 2500	2.4	25	±1.5	-1	+8	1.2/1.7	12	17
LNA-2535	500- 2500	0.6	35	±1.6	+25	+38.5	1.5/1.5	12	230
LNA-2550	1000- 2500	1.1	33	±1.0	+19	+35	1.2/1.2	12	175
LNA-2600	2500- 2700	1.8	20	±0.4	+10	+20	2.3/1.5	12	45
LNA-2700	2200- 3200	1.7	20	±0.75	+10	+20	2.5/1.5	12	45
LNA-3000A	40- 3000	1.3	16	±1.6	+7	+22	1.5/1.5	3	18
LNA-3000B	40- 3000	1.3	17.5	±1.6	+19	+32	2.0/2.0	5	60
LNA-3000C	40- 3000	1.3	17.5	±1.6	+19	+32	2.0/2.0	12	60
LNA-3010	750- 2500	1.0	40	±1.6	+20	+33	1.8/1.3	12	140
LNA-3020	1000- 4000	1.0	35	±1.5	+20	+34	3.0/1.7	12	145
LNA-3030	1000- 3000	1.0	40	±1.5	+21	+36	2.5/2.5	12	175
LNA-3035	1000- 3000	0.6	35	±0.6	+25	+38.5	1.7/1.6	12	230
LNA-3040	3000- 4000	1.0	17.5	±3.5	+18.5	+33.7	1.8/1.4	5	65
LNA-4000	3000- 5000	2.0	20	±3.2	+4.5	+15	1.8/1.1	12	20
LNA-4020	20- 4000	2.0	25	±3.2	+12	+27	1.8/1.4	12	135
LNA-4050	20- 4000	2.0	25	±0.7	+18	+34	1.6/1.5	5	160
LNA-4560	4500- 6000	1.1	15	±1.25	+18.4	+31.2	2.5/1.5	5	65
LNA-5200	5100- 5300	2.0	16	±0.3	+12	+24	1.5/1.5	12	55
LNA-5500	5000- 6000	2.0	16	±0.5	+12	+24	1.5/1.6	12	55
LNA-5800	5700- 5900	2.0	16	±0.2	+12	+24	1.7/1.4	12	55
LNA-6500	5800- 6500	2.5	18	±0.75	+14	+27	1.6/2.0	12	88
LNA-6G	500- 6000	1.8	22	±4.2	+4	+15	1.3/1.4	12	15
LNA-8G	1000- 8000	1.6	24	±5.5	+6.3	+16	1.5/1.2	12	20
LNA-14G	7000- 14000	1.8	17	±1.5	+13	+25	1.5/1.5	5	60

Low Noise Amplifier ENA Series

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
ENA-100T	10 – 600	0.9	40	±0.8	+19	+34	1.6/1.3	9 - 15	140
ENA-120T	400 – 1000	0.7	40	±2.0	+17	+31	1.2/1.9	9 - 15	140
ENA-130T	20 – 1000	1.3	30	±0.8	+19	+34	1.4/1.2	9 - 15	140
ENA-150T	20 – 600	2.0	30	±0.8	+19	+34	2.1/1.5	9 - 15	140
ENA-157T	6000 – 18000	2.2	25	±1.7	+11	+24	2.3/1.5	5 - 15	70
ENA-160T	10 – 800	2.1	60	±1.5	+17	+27	2.0/1.5	12 - 15	70
ENA-200T	100 – 2000	2.5	60	±1.0	+19	+33	2.5/1.5	12 - 15	70
ENA-545T	350 – 2350	1.2	30	±3.5	+21	+33	1.5/1.3	9 - 15	160
ENA-750T	500 – 1000	0.85	30	±0.5	+21	+33	1.6/1.3	9 - 15	160
ENA-1721T	1700 – 2100	1.0	22	±1.0	+20	+32	1.4/1.9	9 - 15	160

Low Noise Amplifier GNA Series

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
GNA-60F	10 – 600	0.7	22	±1.1	+19	+33	1.5/1.4	5 - 15	65
GNA-70F	1500 – 6000	1.5	25	±1.0	+12	+25	1.8/1.7	5 - 15	50
GNA-80F	5000 – 11000	1.7	23	±0.5	+12	+22	1.2/1.9	5 - 15	50
GNA-90F	4000 – 12000	1.7	20	±1.7	+12	+22	1.2/1.9	5 - 15	50
GNA-100F	6000 – 14000	2.0	17	±0.8	+13	+25	1.3/1.3	5 - 15	60
GNA-101F	1700 – 2500	0.55	17	±0.3	+17.5	+36	1.4/1.3	5 - 15	115
GNA-102F	1000 – 3000	0.55	17	±0.6	+14	+33	1.3/1.2	5 - 15	115
GNA-103F	1500 – 3500	0.7	17	±0.3	+16.5	+34	1.6/1.5	5 - 15	115
GNA-104F	800 – 4000	0.7	17	±0.7	+13	+32	1.6/1.5	5 - 15	115
GNA-105T	400 – 2500	1.0	17	±3.0	+22	+34	1.8/1.5	9 - 15	50
GNA-106T	1700 – 2100	0.8	15	±0.7	+22	+33	1.8/1.6	9 - 15	50

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
GNA-107T	600 – 1200	0.8	17	±1.25	+20	+32	1.2/1.2	9 - 15	50
GNA-108T	1000 – 2000	0.6	20	±0.5	+20	+36	1.5/1.3	9 - 15	65
GNA-109T	700 – 2700	0.7	21	±1.0	+18	+35	1.4/1.2	9 - 15	65
GNA-110T	1200 – 2700	0.6	20	±1.0	+18	+35	1.7/1.1	9 - 15	65
GNA-111T	1000 – 3500	0.6	20	±0.7	+17	+34	1.9/1.1	9 - 15	65
GNA-112T	500 – 4000	0.7	20	±2.5	+17	+34	1.8/1.2	9 - 15	65
GNA-115T	400 – 2000	0.4	19	±5.5	+21	+36	1.5/1.6	9 - 15	80
GNA-116T	500 – 1000	0.4	21	±2.0	+21	+36	1.6/1.6	9 - 15	80
GNA-117T	100 – 1500	0.4	20	±6.0	+19	+33	1.5/1.7	9 - 15	80
GNA-118T	1800 – 3800	0.8	18	±0.4	+21	+39	1.8/1.6	9 - 15	110
GNA-119T	1000 – 4000	0.8	18	±1.2	+20	+41	1.6/1.5	9 - 15	120
GNA-120F	8000 – 16000	1.9	20	±1.7	+13	+25	1.4/1.1	5 - 15	65
GNA-130F	5000 – 21000	2.5	19	±3.0	+10	+20	1.8/1.3	5 - 15	65
GNA-157F	6000 – 18000	1.9	26	±2.5	+11	+25	2.0/1.6	5	65
GNA-515E	5000 – 15000	1.9	27	±1.9	+10	+25	1.7/1.5	5	65
GNA-612E	6000 – 12000	2.1	24	±0.7	+11	+25	1.4/1.4	5	65
GNA-700F	17000 – 27000	2.4	18	±1.4	+12	+23	2.5/1.4	5 - 15	65
GNA-902F	5000 – 10000	2.0	19	±0.9	+16	+28	1.1/1.3	5	78
GNA-903F	5000 – 17000	1.9	18	±1.8	+14	+25	1.2/1.4	5	100
GNA-904F	24000 – 36000	3.0	22	±3.0	+11	+21	1.3/1.7	5	80

Low Noise Amplifier WNA Series

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
WNA-120	1000 – 3500	1.0	40	±1.0	+18	+34	2.0/1.2	7 - 15	115
WNA-130	400 – 6000	2.0	40	±1.0	+20	+30	1.8/2.0	9 - 15	160
WNA-150	2000 – 6000	2.5	30	±0.8	+18	+30	1.6/1.6	9 - 15	150
WNA-180	10 – 8000	2.5	40	±1.5	+20	+30	1.8/2.5	9 - 15	160
WNA-200	4000 – 8000	1.5	20	±0.8	+18	+28	1.5/1.6	12 - 15	85
WNA-220	10 – 10000	3.5	25	±1.8	+16	+27	1.5/1.8	5 - 15	125
WNA-250	20 – 10000	2.5	30	±2.5	+18	+30	1.7/1.5	9 - 15	150

Low Noise Amplifier BNA Series

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
BNA-1575	1555 – 1595	1.1	33	±0.5	+3	+15	1.5/1.5	5 - 15	10
BNA-1960	1930 – 1990	2.0	43	±0.8	+4	+15	3.0/2.0	9 - 15	30
BNA-2400	2400 – 2500	1.8	20	±0.3	+4	+15	2.2/2.2	9 - 15	18
BNA-2450	2400 – 2500	2.0	40	±2.0	+4	+15	1.8/1.5	9 - 15	30

Low Noise Outdoor Amplifier ODA Series

Part Number	Frequency (MHz)	NF (dB)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
ODA-100	10 – 600	1.2	20	±2.0	+18	+31	1.7/1.3	12 - 15	75
ODA-200	50 – 1250	1.0	17	±2.5	+17	+30	1.2/1.2	12 - 15	75
ODA-300	20 – 2500	1.2	17	±2.3	+18	+30	1.6/1.6	12 - 15	75

Low Power Amplifier LPA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	NF (dB)	VSWR (In/Out)	DC (V)	DC (mA)
LPA-1-18	800 – 1000	18.5	±1.5	+27	+37	4.2	2.2/2.2	5	250
LPA-1-20	50 – 1000	20	±0.3	+20	+36	3.6	1.2/1.3	12	85
LPA-1-30	5 – 1000	32	±1.0	+8.5	+19	3.5	2.2/1.5	5	25
LPA-1-40	10 – 1500	40	±0.5	+20	+32	3.6	1.3/1.4	12	135
LPA-1-45	100 – 1000	45	±0.3	+20	+34	3.5	1.5/1.5	12	135
LPA-2-15	5 – 2400	20	±2.5	+9	+18	6.0	1.6/2.5	3	37
LPA-2-17	50 – 2500	17	±1.5	+18.5	+32.5	4.0	1.5/1.5	12	85
LPA-2-19	5 – 2000	21.5	±1.5	+7.8	+18.5	6.0	1.6/1.9	5	27
LPA-2-20	50 – 3000	21	±4.0	+8	+18	6.5	1.8/2.2	3	28
LPA-2-30	100 – 2100	21	±0.5	+18	+32	4.2	1.5/1.2	12	130
LPA-3-10	50 – 3000	11.5	±2.0	+17.5	+32.5	4.4	1.2/1.3	12	80
LPA-3-13	0.01 – 3000	13	±1.5	+13	+26	4.0	1.2/1.5	15	47
LPA-3-15	10 – 3000	18	±4.0	+20	+33	3.3	1.7/1.9	12	115
LPA-3-18	1 – 3000	18	±1.5	+22	+35	4.0	1.5/2.0	15	110
LPA-3-24	50 – 3000	24	±0.5	+14	+24	4.5	1.4/1.5	12	95
LPA-4-14	10 – 4000	18	±8.0	+20	+34	3.5	1.5/2.0	12	80
LPA-4-15	100 – 5000	15	±0.75	+19	+35	4.5	1.5/1.5	12	85
LPA-4-18	60 – 4000	20	±1.5	+20	+35	4.2	1.5/1.5	5	75
LPA-4-30	100 – 4000	33	±1.5	+18.7	+34	5.0	1.7/1.6	12	130
LPA-4-34	50 – 4000	34	±1.5	+19	+34	4.1	1.6/1.8	12	130
LPA-5-15	70 – 5500	15	±0.5	+19	+35	4.5	1.5/1.5	5	80
LPA-6-12	100 – 6000	15	±1.7	+12.5	+26	4.0	2.0/2.3	12	40
LPA-6-13	1000 – 6000	13	±2.0	+12	+23	7.0	1.8/1.5	12	45
LPA-6-23	1000 – 6000	23	±2.0	+15	+27	7.0	1.4/1.6	12	105
LPA-6-26	100 – 6000	34	±4.5	+19	+32	4.2	2.0/2.0	12	125

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	NF (dB)	VSWR (In/Out)	DC (V)	DC (mA)
LPA-6-27	50 – 6000	27	±1.75	+16.9	+31	5.5	1.7/1.8	12	130
LPA-6-30	0.3 – 6500	35	±4.5	+17	+29	4.0	1.4/1.6	12	120
LPA-7-24	100 – 7000	24	±1.5	+16	+28	5.5	1.3/1.8	12	130
LPA-7-25	0.1 – 7000	37	±5.75	+19	+31	4.2	1.7/1.7	12	130
LPA-8-17	10 – 8000	21	±3.25	+17	+32	3.5	1.2/1.2	12	75
LPA-9-22	50 – 9000	32	±5.75	+15.3	+28.1	4.5	1.7/1.5	12	110
LPA-10-10	100 – 10000	16	±3.1	+13	+28	4.0	1.7/1.7	12	50
LPA-10-20	0.1 – 10000	27	±6.5	+13	+26	5.0	1.7/1.7	12	110

Low Power Amplifier EPA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	NF (dB)	VSWR (In/Out)	DC (V)	DC (mA)
EPA-140T	100 – 3000	43	±1.3	+18	+35	3.6	1.7/1.7	12 - 15	190
EPA-150T	50 – 3000	50	±1.8	+14	+28	3.6	1.3/1.3	9 - 15	155
EPA-158T	6000 – 12000	19	±1.1	+19	+26	5.5	1.6/1.9	9 - 15	105
EPA-160T	100 – 8000	30	±3.0	+10	+23	6.0	1.3/1.6	12 - 15	120
EPA-240T	50 – 6000	37	±1.2	+18	+33	5.0	1.3/1.5	12 - 15	180
EPA-250T	30 – 9000	40	±1.7	+14	+26	5.3	1.2/1.3	12 - 15	150
EPA-270T	30 – 2700	43	±3.0	+25	+35	4.0	1.4/1.2	12	300

Low Power Amplifier GPA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	NF (dB)	VSWR (In/Out)	DC (V)	DC (mA)
GPA-101T	4000 – 12000	18	±3.0	+16	+27	5.0	2.4/1.4	11 - 18	45
GPA-102T	8000 – 16000	13	±2.5	+16	+27	4.5	1.5/1.4	11 - 18	45
GPA-183F	5000 – 18000	13	±1.5	+17	+25	4.8	1.3/1.3	5	145
GPA-200F	2000 – 20000	20	±3.0	+12	+26	6.5	1.2/1.5	5	100
GPA-240F	5000 – 20000	10	±1.3	+17	+25	6.5	1.3/1.3	5	130
GPA-280F	20000 – 36000	24	±3.0	+11	+21	3.3	1.4/2.1	5	80
GPA-512E	5000 – 12000	11	±0.4	+17	+25	6.5	1.3/1.4	5	130
GPA-612E	5000 – 12000	13	±0.7	+17	+25	4.8	1.3/1.5	5	145

Low Power Amplifier LRA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	NF (dB)	VSWR (In/Out)	DC (V)	DC (mA)
LRA-69	10 – 1000	25	±0.6	+20	+33	4.0	1.3/1.5	15	125
LRA-77	5 – 600	16	±0.3	+18	+32	4.0	1.5/1.4	15	56
LRA-82	10 – 300	25	±0.7	+20	+31	2.8	1.5/1.6	15	50
LRA-151	3 – 600	13	±1.0	+22	+34	4.5	1.5/1.6	15	85

DC Coupled Amplifier DCA Series

Part Number	Frequency (MHz)	Power Gain (dB)	Voltage Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	VSWR (In/Out)	DC (V)	DC (mA)
DCA-50-08	DC – 2000	8	5	±1.5	+11	+25	-25dB	± 12	± 45
DCA-50-14	DC – 1500	14	10	±1.5	+11	+25	-23dB	± 12	± 45
DCA-50-20	DC – 50	20	20	±0.3	+14	+24	1.1/1.1	12	45
DCA-50-23	DC – 40	27	45	±1.3	+14	+24	1.1/1.15	12	45
DCA-50-27	DC – 34	23	30	±1.5	+14	+25	1.1/1.1	± 12	± 25
DCA-50-28	DC – 27	23	30	±1.5	+14	+25	1.1/1.1	± 5	± 20
DCA-50-30	DC – 17	30	64	±1.5	+14	+25	1.1/1.1	12	45
DCA-50-33	DC – 15	33	90	±1.5	+14	+25	1.1/1.1	± 5	± 20
DCA-50-40	DC – 6.5	40	200	±1.5	+14	+25	1.1/1.1	± 12	± 25
DCA-50-50	DC – 1.7	50	630	±0.5	+14	+25	1.1/1.1	± 12	± 25
DCA-50-60	DC – 0.5	60	2000	±1.5	+14	+25	1.1/1.1	± 12	± 25

REBES
 Interconnect System

Medium Power Amplifier MGA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	NF (dB)	VSWR (In/Out)	DC (V)	DC (mA)
MGA-250	225 – 275	25	±0.5	+28	+41	4.5	1.5/1.1	5	470
MGA-430	400 – 470	14	±0.3	+30	+44	6.5	1.3/1.2	12	360
MGA-500	10 – 1000	27	±1.2	+26	+27.5	5.8	1.5/2.5	12	230
MGA-900	800 – 1000	15	±0.5	+29	+47	8.0	1.2/-	5	700
MGA-930	800 – 1000	30	±0.75	+30	+47	5.5	1.3/-	5	700
MGA-1600	1500 – 1700	12	±0.5	+30	+43.5	6.0	1.4/1.4	5	750
MGA-1750	1500 – 2000	25	±0.5	+30	+39	7.3	1.4/1.8	5	530
MGA-1850	1750 – 1950	12	±0.5	+30	+47	5.5	1.7/1.6	5	750
MGA-2000	1600 – 2400	26	±2.5	+27	+42	7.2	1.5/1.7	5	550
MGA-2500	2000 – 3000	24	±1.75	+28.5	+42	6.0	1.7/1.9	5	480
MGA-3500	3000 – 4000	20	±1.75	+27	+39	5.0	1.2/1.2	5	430
MGA-1-40	50 – 1500	40	±1.0	+24	+37	3.5	1.2/1.6	12	200
MGA-2-24	300 – 2500	24	±2.0	+23	+34	5.0	1.5/1.3	12	200
MGA-2-30	50 – 2500	30	±2.5	+25	+38	4.8	1.2/1.3	12	230
MGA-3-27	30 – 3000	27	±3.5	+25	+38.5	3.8	1.5/1.5	12	220
MGA-4-27	50 – 4000	27	±1.5	+20	+35	4.7	1.6/1.8	12	160
MGA-4-33	50 – 4500	33	±2.0	+21	+35	4.5	1.4/1.8	12	160
MGA-5-30	100 – 5000	30	±0.5	+20	+34	5.0	1.3/2.3	12	170
MGA-5150	4850 – 5450	20	±2.0	+27	+39	6.0	1.6/-	5	900
MGA-5250	5150 – 5350	20	±1.5	+27.3	+40	6.0	1.6/-	5	900
MGA-22-13	1000 – 22000	13	±1.2	+22	+32	6.0	1.7/1.7	12	225

Medium Power Amplifier MPA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	NF (dB)	VSWR (In/Out)	DC (V)	DC (mA)
MPA-370	270 – 470	35	±1.5	+36	+45	6.0	1.3/1.3	9	1650
MPA-450	300 – 600	40	±0.5	+38	+46	6.0	1.4/1.4	24	880
MPA-0709	700 – 900	42	±1.5	+37	+47	8.0	1.2/2.0	9	1600
MPA-0850	750 – 950	40	±1.0	+37	+47	6.0	2.0/2.0	9	1650
MPA-0880	800 – 960	36	±0.8	+33	+47	1.3	1.5/1.2	12	1100
MPA-0915	902 – 928	40	±0.1	+37	+47	6.0	1.3/1.5	9	1650
MPA-0925	850 – 1000	40	±1.0	+37	+47	6.0	1.3/1.5	9	1650
MPA-0950	750 – 1150	28	±1.0	+30	+40	6.0	2.3/1.5	12	1000
MPA-1400	1300 – 1500	32	±0.5	+31.7	+41	5.5	1.3/1.6	12	1000
MPA-1600	1500 – 1700	30	±1.0	+30	+41	5.5	1.3/1.5	12	970
MPA-16-33	1500 – 1700	33	±0.5	+30	+40	1.5	1.5/2.5	12	800
MPA-2200	2190 – 2210	40	±0.2	+33	+42	2.5	1.5/1.5	9	670
MPA-10-40	1 – 1000	40	±1.5	+30	+40	3.3	1.3/1.2	12	360
MPA-11-40	2 – 1000	40	±1.8	+30	+45	4.2	1.5/1.2	12	420
MPA-22-30	30 – 2200	30	±1.0	+30	+41	4.2	1.4/1.2	12	415
MPA-24-20	2400 – 2500	28	±1.0	+33	+42	6.0	1.2/2.0	12	800
MPA-36-23	3200 – 4000	23	±0.5	+33	+42	7.5	1.8/1.3	5	1300
MPA-36-35	3200 – 4000	35	±1.0	+32	+42	6.0	1.3/1.3	5	1300
MPA-40-40	20 – 1000	40	±0.5	+36	+47	6.0	1.5/1.5	24	630
MPA-54-30	4800 – 6000	30	±1.0	+30	+39	6.0	1.4/2.7	12	550
MPA-58-30	5700 – 5900	30	±1.0	+30	+39	6.0	1.8/2.1	12	600
MPA-75-30	6000 – 9000	30	±1.5	+30	+40	6.0	1.5/3.0	12	1400

Medium Power Amplifier MRA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{1dB} (dBm)	IP3 (dBm)	NF (dB)	VSWR (In/Out)	DC (V)	DC (mA)
MRA-512	10 – 1000	18	±0.5	+27	+39	6.0	1.4/1.4	15	210

High Power Amplifier HPA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{out} (Watt)	P _{sat} (Watt)	IP3 (dBm)	VSWR (Input)	DC (V)	DC (mA)
HPA-155	135 – 175	37.5	±2.0	20	28	-	1.5:1	12	3200
HPA-250	30 – 512	30.0	-	10	-	-	1.1:1	28	1000
HPA-300	30 – 600	30.0	-	10	-	-	1.2:1	12	2900
HPA-480	440 – 520	38.5	±1.0	20	28	-	1.8:1	12	2800
HPA-820	760 – 880	39.5	±1.0	16	20	-	1.5:1	12	3200
HPA-850	750 – 950	40	±1.0	10	16	+48	1.4:1	12	2750
HPA-900A	850 – 950	40	±0.5	10	16	+48	1.4:1	12	2750
HPA-910	880 – 940	30	±1.0	10	16	+50	1.5:1	12	2500
HPA-915	902 – 928	40	±0.5	10	16	+50	1.4:1	12	2500
HPA-1820	1800 – 2000	30	±1.0	10	17	+48	1.2:1	28	1550

High Power Amplifier SPA Series

Part Number	Frequency (MHz)	Gain (dB)	Gain Flatness (dB)	P _{out} (Watt)	P _{out} (dBm)	IP3 (dBm)	VSWR (Input)	DC (V)	DC (mA)
SPA-775	700 – 850	43	±1.5	10	+40	+49	1.3:1	12	2750
SPA-800	700 – 900	43	±1.5	10	+40	+49	1.3:1	12	2700
SPA-850	750 – 950	43	±1.0	10	+40	+49	1.3:1	12	2500
SPA-860	760 – 960	40	±1.7	10	+40	+50	1.3:1	12	2750
SPA-915	902 – 928	40	±0.5	10	+40	+50	1.2:1	12	2850

SPA-925	900 – 950	40	± 0.5	10	+40	+50	1.2:1	12	2750
---------	-----------	----	-----------	----	-----	-----	-------	----	------

Custom Frequency Divider/Prescaler FBS Series

Part Number	Input Frequency (MHz)	Function Divide Ratio	Input Power (dBm)	Output Power (dBm)	100KHz SSB Phase Noise (dBc/Hz)	DC Voltage (V)	DC Current (mA)
FBS-N-14	100 – 14000	$\div N$ (8 to 511)	-15 to +10	+1	-150	5	315
FBS-N-15	100 – 15000	$\div N$ (2 to 500000)	-15 to +10	0	-147	5	230

Custom Frequency Divider/Prescaler FAS/FCS/FDS Series (N=2 to 256)

Part Number	Input Frequency (MHz)	Function Divide Ratio	Input Power (dBm)	Output Power (dBm)	100KHz SSB Phase Noise (dBc/Hz)	DC Voltage (V)	DC Current (mA)
FAS-N	0.1 – 50	$\div N$ (2 to 256)	-20 to +17	+12	-144	12	70
FCS-N	0.1 – 50	$\div N$ (2 to 256)	-20 to +17	TTL/CMOS	-144	12	70
FDS-N	DC – 50	$\div N$ (2 to 256)	TTL/CMOS	TTL/CMOS	-144	12	70

Frequency Divider/Prescaler FPS Series

Part Number	Input Frequency (GHz)	Function Divide Ratio	Input Power (dBm)	Output Power (dBm)	100KHz SSB Phase Noise (dBc/Hz)	DC Voltage (V)	DC Current (mA)
FPS-2-18	0.2 – 18	$\div 2$	-15 to +10	-4	-150	12	80
FPS-2-20	0.1 – 20	$\div 2$	-9 to +10	0	-153	5	160
FPS-4-18	0.2 – 18	$\div 4$	-15 to +10	-4	-150	12	100
FPS-4-20	0.1 – 20	$\div 4$	-9 to +10	0	-153	5	170
FPS-4-26	10 – 26	$\div 4$	-9 to +10	0	-153	5	170
FPS-5-15	0.1 – 15	$\div 5$	-19 to +10	+3	-153	5	205
FPS-6-15	0.1 – 15	$\div 6$	-20 to +10	+4	-153	5	205
FPS-7-15	0.1 – 15	$\div 7$	-23 to +10	+4	-153	5	205
FPS-8-18	0.2 – 18	$\div 8$	-15 to +10	-4	-150	12	105
FPS-8-20	0.1 – 20	$\div 8$	-9 to +10	0	-153	5	175

FPS-9-15	0.1 – 15	$\div 9$	-17 to +10	+4	-153	5	205
FPS-2-12	0.1 – 12.5	$\div 2$	-15 to +10	+4	-145	12	105
Part Number	Input Frequency (GHz)	Function Divide Ratio	Input Power (dBm)	Output Power (dBm)	100KHz SSB Phase Noise (dBc/Hz)	DC Voltage (V)	DC Current (mA)
FPS-4-13	0.1 – 13	$\div 4$	-15 to +10	+5	-151	12	120
FPS-6-12	0.1 – 12.5	$\div 6$	-15 to +10	-1	-144	12	175
FPS-8-12	0.1 – 12	$\div 8$	-15 to +10	-6	-153	12	70
FPS-10-12	0.1 – 12	$\div 10$	-15 to +10	-1	-144	12	185
FPS-12-13	0.1 – 13	$\div 12$	-15 to +10	-1	-145	12	185
FPS-20-13	0.1 – 13	$\div 20$	-15 to +10	-1	-145	12	195
FPS-24-12	0.1 – 12	$\div 24$	-15 to +10	-1	-147	12	140
FPS-40-12	0.1 – 12	$\div 40$	-15 to +10	-1	-147	12	150
FPS-3-8	0.1 – 8	$\div 3$	-12 to +12	-1	-153	12	70
FPS-5-8	0.1 – 8	$\div 5$	-12 to +12	-1	-153	12	80
FPS-9-8	0.1 – 8	$\div 9$	-12 to +12	-1	-147	12	170
FPS-15-8	0.1 – 8	$\div 15$	-12 to +12	-1	-147	12	150
FPS-25-8	0.1 – 8	$\div 25$	-12 to +12	-1	-147	12	160
FPS-64-8	0.8 – 8	$\div 64$	-10 to +10	0	-144	12	75
FPS-72-8	0.8 – 8	$\div 72$	-10 to +10	0	-144	12	75
FPS-80-8	0.8 – 8	$\div 80$	-10 to +10	-1.5	-144	12	70
FPS-128-8	0.8 – 8	$\div 128$	-10 to +10	0	-144	12	75
FPS-136-8	0.8 – 8	$\div 136$	-10 to +10	0	-144	12	75
FPS-160-8	0.8 – 8	$\div 160$	-10 to +10	0	-144	12	70
FPS-256-8	0.8 – 8	$\div 256$	-10 to +10	0	-144	12	75
FPS-264-8	0.8 – 8	$\div 264$	-10 to +10	-1	-144	12	75
FPS-320-8	0.8 – 8	$\div 320$	-10 to +10	-1.5	-144	12	70
FPS-512-8	0.8 – 8	$\div 512$	-10 to +10	-1	-144	12	75
FPS-520-8	0.8 – 8	$\div 520$	-10 to +10	-1	-144	12	75

FPS-640-8	0.8 – 8	$\div 640$	-10 to +10	-1.5	-144	12	70
FPS-1016-8	0.8 – 8	$\div 1016$	-10 to +10	-1.5	-144	12	70
Part Number	Input Frequency (GHz)	Function Divide Ratio	Input Power (dBm)	Output Power (dBm)	100KHz SSB Phase Noise (dBc/Hz)	DC Voltage (V)	DC Current (mA)
FPS-1024-8	0.8 – 8	$\div 1024$	-10 to +10	-1.5	-144	12	70
FPS-2040-8	0.8 – 8	$\div 2040$	-10 to +10	-1.5	-144	12	70
FPS-45-6	0.5 – 6	$\div 45$	-12 to +12	0	-144	12	85
FPS-50-6	0.5 – 6	$\div 50$	-12 to +12	0	-144	12	85
FPS-85-6	0.5 – 6	$\div 85$	-12 to +12	0	-144	12	85
FPS-100-6	0.5 – 6	$\div 100$	-12 to +12	-1.5	-144	12	85
FPS-165-6	0.5 – 6	$\div 165$	-12 to +12	-1.5	-144	12	85
FPS-200-6	0.5 – 6	$\div 200$	-12 to +12	-1.5	-144	12	85
FPS-325-6	0.5 – 6	$\div 325$	-12 to +12	-1	-144	12	85
FPS-400-6	0.5 – 6	$\div 400$	-12 to +12	-1.5	-144	12	85
FPS-635-6	0.5 – 6	$\div 635$	-12 to +12	-1	-144	12	85
FPS-1275-6	0.5 – 6	$\div 1275$	-12 to +12	-1	-144	12	85
FPS-1280-6	0.5 – 6	$\div 1280$	-12 to +12	-1	-144	12	85
FPS-16-4	0.4 – 4	$\div 16$	-10 to +10	-1	-144	12	75
FPS-27-4	0.3 – 4	$\div 27$	-12 to +12	0	-144	12	75
FPS-30-4	0.3 – 4	$\div 30$	-12 to +12	-1.5	-144	12	75
FPS-32-4	0.4 – 4	$\div 32$	-10 to +10	0	-144	12	75
FPS-36-4	0.4 – 4	$\div 36$	-10 to +10	0	-144	12	75
FPS-48-4	0.3 – 4	$\div 48$	-10 to +10	0	-144	12	75
FPS-51-4	0.3 – 4	$\div 51$	-10 to +10	0	-144	12	75
FPS-60-4	0.3 – 4	$\div 60$	-10 to +10	-1.5	-144	12	75
FPS-68-4	0.4 – 4	$\div 68$	-10 to +10	0	-144	12	75
FPS-96-4	0.3 – 4	$\div 96$	-12 to +12	-1	-144	12	75
FPS-99-4	0.3 – 4	$\div 99$	-12 to +12	-1	-144	12	75

FPS-120-4	0.3 – 4	÷120	-12 to +12	-1.5	-144	12	75
FPS-132-4	0.4 – 4	÷132	-10 to +10	-1	-144	12	75
Part Number	Input Frequency (GHz)	Function Divide Ratio	Input Power (dBm)	Output Power (dBm)	100KHz SSB Phase Noise (dBc/Hz)	DC Voltage (V)	DC Current (mA)
FPS-192-4	0.3 – 4	÷192	-12 to +12	-1	-144	12	75
FPS-195-4	0.3 – 4	÷195	-12 to +12	-1	-144	12	75
FPS-240-4	0.3 – 4	÷240	-12 to +12	-1.5	-144	12	75
FPS-260-4	0.4 – 4	÷260	-12 to +12	-1	-144	12	75
FPS-381-4	0.3 – 4	÷381	-10 to +10	-1	-144	12	75
FPS-384-4	0.3 – 4	÷384	-10 to +10	-1	-144	12	75
FPS-508-4	0.4 – 4	÷508	-10 to +10	-1	-144	12	75
FPS-765-4	0.3 – 4	÷765	-12 to +12	-1	-144	12	75
FPS-768-4	0.3 – 4	÷768	-12 to +12	-1	-144	12	75
FPS-1020-4	0.4 – 4	÷1020	-10 to +10	-1	-144	12	75

Frequency Doubler FDR/QDR Series

Part Number	Input Frequency (GHz)	Output Frequency (GHz)	Input Power (dBm)	Conversion Loss (dB)	Harmonic Output F ₀ (dBc)	Harmonic Output F ₃ (dBc)	Harmonic Output F ₄ (dBc)
FDR-1-2	0.01 – 1	0.02 – 2	+12 to +16	15	35	42	20
FDR-2-4	0.85 – 2	1.7 – 4	+10 to +20	15	45	52	40
FDR-3-6	1.25 – 3	2.5 – 6	+10 to +20	15	40	45	42
FDR-4-8	2 – 4	4 – 8	+10 to +15	13	33	42	40
FDR-8-16	4 – 8	8 – 16	+10 to +15	16	41	46	40
QDR-1	0.85 – 2	1.7 – 4	+10 to +20	15	45	52	40
QDR-2	1.25 – 3	2.5 – 6	+10 to +20	15	40	45	42
QDR-3	2 – 4	4 – 8	+10 to +15	13	33	42	40
QDR-4	4 – 8	8 – 16	+10 to +15	16	41	46	40

Frequency Tripler FMR/FTR Series

Part Number	Input Frequency (MHz)	Output Frequency (MHz)	Input Power (dBm)	Conversion Gain (dB)	Harmonic Output F ₀ /F ₂ /F ₄ (dBc)	DC Voltage (V)	DC Current (mA)
FMR-3-1	250 - 350	750 - 1050	-3	7	40/35/55	12	105
FMR-3-2	320 - 450	960 - 1350	-3	6	40/35/40	12	105
FMR-3-3	450 - 600	1350 - 1800	-3	9	35/30/40	12	105
FMR-3-4	600 - 750	1800 - 2250	-3	4	45/30/25	12	105
FMR-3-5	700 - 1000	2100 - 3000	0	12	25/25/40	12	150
FMR-3-6	1000 - 1500	3000 - 4500	+9	0	20/20/30	12	150
FTR-835	274 - 284	822 - 852	0	10	93/89/88	12	150
FTR-880	289 - 299	867 - 897	0	9.5	93/103/100	12	150
FTR-915	300 - 310	900 - 930	0	13	60/85/100	12	150
FTR-945	310 - 320	930 - 960	0	11.5	30/60/72	12	150
FTR-1845	600 - 630	1800 - 1890	0	12	35/43/65	12	160
FTR-2450	800 - 833	2400 - 2499	0	12	25/42/78	12	160

Frequency Multiplier X5 FVR Series

Part Number	Input Frequency (MHz)	Output Frequency (MHz)	Input Power (dBm)	Conversion Gain (dB)	Harmonic Output F ₀ /F ₂ /F ₄ /F ₆ (dBc)	DC Voltage (V)	DC Current (mA)
FVR-835	164 - 170	820 - 850	0	2	90/85/95/98	12	150
FVR-880	173 - 179	865 - 895	0	2	90/83/96/97	12	150
FVR-915	180 - 186	900 - 930	0	2	60/48/95/98	12	150
FVR-945	186 - 192	930 - 960	+3	-3	33/34/62/87	12	150
FVR-1845	360 - 378	1800 - 1890	-5	7.5	40/30/45/65	12	170
FVR-2450	480 - 500	2400 - 2500	0	9	31/37/72/83	12	160

Frequency Mixer MXR Series

Part Number	Frequency LO/RF (MHz)	Frequency IF (MHz)	LO Level (dBm)	Conversion Loss (dB) Mid-Band	Conversion Loss (dB) Max.	Isolation LO/RF (dB) Mid-Band	Isolation LO/IF (dB) Mid-Band	Input IP3 (dBm) Mid-Band
MXR-2H	220 - 300	DC - 80	+17	7.5	8.5	45	38	+26
MXR-5	0.5 - 500	DC - 500	+10	6.5	8.2	55	45	+15
MXR-5E	2 - 500	DC - 500	+7	6.0	8.0	45	45	+16
MXR-5J	2 - 500	DC - 500	+10	6.0	8.0	45	45	+16
MXR-10	5 - 1000	DC - 1000	+7	7.0	8.0	47	45	+20
MXR-10E	20 - 1000	DC - 1000	+7	7.0	8.0	50	47	+17
MXR-10F	10 - 1000	DC - 1000	+10	6.5	8.2	48	35	+16
MXR-10L	10 - 1000	DC - 800	+4	7.2	8.2	60	33	+16
MXR-10M	5 - 1000	DC - 1000	+13	7.0	9.5	39	30	+22
MXR-12M	10 - 1200	DC - 1200	+13	8.0	8.5	45	42	+22
MXR-15	5 - 1500	DC - 1000	+7	7.5	9.3	40	40	+15
MXR-15H	10 - 1500	DC - 1500	+17	7.0	8.5	35	35	+26
MXR-17H	100 - 1700	50 - 1500	+17	7.0	8.5	34	35	+25
MXR-20	350 - 2000	DC - 400	+7	7.0	9.2	36	29	+13
MXR-20E	1500 - 2000	DC - 300	+7	6.0	8.0	31	28	+14
MXR-22H	10 - 2200	DC - 1800	+17	6.5	8.0	32	35	+25
MXR-23M	2050 - 2350	DC - 300	+13	7.2	8.0	30	27	+26
MXR-25	1400 - 2500	DC - 500	+7	7.5	9.0	30	25	+13
MXR-25DM	40 - 2500	DC - 1000	+13	8.0	9.0	37	35	+26
MXR-25F	100 - 2500	DC - 750	+13	6.5	7.5	35	30	+18
MXR-25M	5 - 2500	5 - 1500	+13	8.5	9.8	34	32	+18
MXR-25H	80 - 2500	1 - 1000	+17	8.0	8.6	37	33	+30
MXR-25W	10 - 2500	10 - 2500	+17	7.2	9.0	42	34	+27.5
MXR-27	1 - 2700	1 - 2000	+10	7.0	9.5	39	36	+20
MXR-27H	1 - 2700	1 - 2000	+17	7.0	9.5	38	31	+27.8

Part Number	Frequency LO/RF (MHz)	Frequency IF (MHz)	LO Level (dBm)	Conversion Loss (dB) Mid-Band	Conversion Loss (dB) Max.	Isolation LO/RF (dB) Mid-Band	Isolation LO/IF (dB) Mid-Band	Input IP3 (dBm) Mid-Band
MXR-35M	5 – 3500	5 – 2500	+13	8.9	10.5	38	28	+18
MXR-36H	1500 – 3600	DC – 600	+17	8.0	9.0	30	34	+25
MXR-42M	5 – 4200	5 – 3500	+13	9.8	11.5	29	26	+17
MXR-42T	800 – 4200	DC – 800	+13	9.0	10.8	35	18	+19
MXR-45M	1500 – 4500	DC – 1500	+13	8.5	10.0	40	35	+19
MXR-60H	2500 – 6000	DC – 2500	+17	8.5	9.7	20	14	+25
MXR-60M	2500 – 6000	DC – 1500	+13	8.5	9.5	28	14	+19
MXR-90M	4500 – 9000	DC – 2500	+13	8.5	10.0	25	25	+21
MXR-150M	9000 – 15000	DC – 2500	+13	8.0	11.0	40	17	+17

Frequency Mixer GXR Series

Part Number	Frequency LO/RF (MHz)	Frequency IF (MHz)	LO Level (dBm)	Conversion Loss (dB)	Isolation LO/RF (dB)	Isolation LO/IF (dB)	Isolation RF/IF (dB)	Input IP3 (dBm)
GXR-1	2000 - 18000	DC – 4000	+13	10	38	20	15	+20
GXR-2	300 - 10000	DC – 4000	+17	9	55	42	20	+23
GXR-3	5500 - 14000	DC – 6000	+15	7	45	25	14	+20
GXR-4	6000 - 26000	DC – 8000	+13	9	37	37	11	+22
GXR-5	7000 - 14000	DC – 5000	+13	8	45	36	30	+22
GXR-6	7000 - 34000	DC – 8000	+15	11	35	40	20	+22
GXR-7	11000 - 20000	DC – 6000	+13	8	46	40	25	+18
GXR-8	14000 - 26000	DC – 8000	+13	9	35	35	30	+20
GXR-9	16000 - 30000	DC – 8000	+13	10	40	34	30	+21
GXR-10	24000 - 32000	DC – 8000	+13	11	38	40	30	+18
GXR-12	5000 - 12000	DC – 4000	+10	9	18	20	20	+21
GXR-13	800 - 2000	DC – 500	+10	9	40	30	22	+16
GXR-14	1500 – 4500	DC – 1500	+13	8.5	40	35	20	+19
GXR-15	4500 – 9000	DC – 2500	+13	9	25	25	20	+21

Part Number	Frequency LO/RF (MHz)	Frequency IF (MHz)	LO Level (dBm)	Conversion Loss (dB)	Isolation LO/RF (dB)	Isolation LO/IF (dB)	Isolation RF/IF (dB)	Input IP3 (dBm)
GXR-16	9000 – 15000	DC – 2500	+13	8.5	40	40	17	+17
GXR-17	6000 – 14000	DC – 5000	+13	6.5	40	22	37	+16
GXR-18	11000 – 22000	DC – 6000	+13	6.0	43	38	25	+16
GXR-19	16000 – 26000	DC – 9000	+13	7.0	40	40	25	+17
GXR-20	20000 – 32000	DC – 10000	+13	7.0	36	36	26	+18

Power Splitter/Combiner 2-Way 0° Resistive PSC-2R Series

Part Number	Frequency (MHz)	Insertion Loss Above 6dB (dB) Mid-Bnd/Max	Isolation Low-Band (dB)	Isolation Upp-Band (dB)	Amplitude Unbalance (dB) max	Phase Unbalance (°) max	Input Power (dBm)
PSC-2R-42	DC - 4200	0.1/0.5	6.2	7.0	0.5	5	+30
PSC-2R-70	DC - 7000	0.2/0.6	6.6	7.2	0.6	5	+30

Power Splitter/Combiner 2-Way 0° PSC-2 Series

Part Number	Frequency (MHz)	Insertion Loss Above 3dB (dB) Mid-Bnd/Max	Isolation Mid-Band (dB)	Isolation Min. (dB)	Amplitude Unbalance (dB) max	Phase Unbalance (°) max	Input Power (dBm)
PSC-2-6	1 - 650	0.3/0.8	30	20	0.3	3	+33
PSC-2-10	5 - 1000	0.4/0.9	28	15	0.3	3	+27
PSC-2-20	20 - 2000	0.7/1.0	18	15	0.7	5	+30
PSC-2-0809	820 - 960	0.4/0.6	23	15	0.1	1.5	+30
PSC-2-1516	1510 - 1660	0.4/0.6	20	15	0.1	3	+30
PSC-2-1719	1510 - 1660	0.3/0.5	20	15	0.1	4	+30
PSC-2-1819	1850 - 1990	0.5/0.6	21	15	0.1	3	+30
PSC-2-2225	2200 - 2500	0.3/0.5	20	15	0.1	5	+30

Directional Coupler DCR Series

Part Number	Frequency (MHz)	Mainline Loss (dB)	Coupling (dB)	Flatness (dB)	Directivity (dB)	VSWR	Input Power (dBm)
DCR-10-4	5 - 1000	0.9	10.5	± 1	35	1.2:1	+30
DCR-15-4	5 - 1000	0.7	15.5	± 0.5	22	1.2:1	+30
DCR-20-4	5 - 1000	0.6	20.0	± 0.8	21	1.2:1	+30

Phase Detector with Loop Filter PDF Series

Part Number	Frequency (MHz)	Input Power (dBm)	Output (V)	Bandwidth (KHz)	Phase Noise (dBc/Hz@1KHz)	DC Power (V)	Current (mA)
PDF-100	3 - 300	-10 to +17	0.1 to 4.9	10	-85	12	175
PDF-150	200 - 800	-7 to +10	0.1 to 4.9	10	-92	12	90
PDF-200	5 - 30	-3 to +17	0.1 to 4.9	10	-90	12	20

Temperature Compensated Crystal Oscillator TCXO Series

Part Number	Frequency (MHz)	Temp Stability (ppm)	Output Format	Operating Temp (°C)	Phase Noise (dBc/Hz@1KHz)	DC Power (V)	Current (mA)
TCXO-10M	10	± 2.5	HCMOS	-30 to +75	-145	9 - 15	10
TCXO-20M	20	± 2.5	HCMOS	-30 to +75	-145	9 - 15	10

Phase Locked Oscillator PLO Series

Part Number	RF Output Frequency (MHz)	RF Output Power (dBm)	Reference Frequency (MHz)	Reference Input Power (dBm)	Internal Divide Ratio	Phase Noise (dBc/Hz@1KHz)	DC Power (Volt/mA)
PLO-1000N	997 - 1003	+17	9.97 – 10.03	-7 to +17	100	-97	12/370
PLO-1050	900 - 1200	+17	9 - 12	+3 to +17	100	-97	12/300
PLO-1540	1435 - 1650	+17	8.97 - 10	+3 to +17	165	-95	12/300
PLO-2050	1950 - 2150	+17	9.75 – 10.75	+3 to +17	200	-93	12/300
PLO-2275	2150 - 2400	+17	8.95 – 10	+3 to +17	240	-92	12/300
PLO-2375	2300 - 2450	+17	9.58 – 10.21	+3 to +17	240	-92	12/300
PLO-2400N	2399 - 2401	+17	9.99 – 10.01	-7 to +17	240	-95	12/370
PLO-3000N	2990 - 3010	+17	9.97 – 10.03	-7 to +17	300	-95	12/370
PLO-3300	3200 - 3400	+15	9.84 – 10.46	+3 to +17	325	-92	12/300

Part Number	RF Output Frequency (MHz)	RF Output Power (dBm)	Reference Frequency (MHz)	Reference Input Power (dBm)	Internal Divide Ratio	Phase Noise (dBc/Hz@1KHz)	DC Power (Volt/mA)
PLO-3500N	3497 - 3503	+17	9.99 – 10.01	-7 to +17	350	-90	12/370
PLO-5300	5150 - 5400	+13	9.9 – 10.4	+3 to +17	520	-78	12/315

Voltage Controlled Oscillator VCO Series

Part Number	Output Frequency (MHz)	Tuning Voltage (Volt)	Tuning Sensitivity (MHz/V)	Output Power (dBm)	SSB Phase Noise (dBc/Hz@10KHz)	DC Power (V)	Current (mA)
VCO-0235	175 - 300	1 - 10	24	+10	-105	12	20
VCO-0350	330 - 370	0.5 – 4.5	14	+5	-97	12	18
VCO-0625	575 - 675	0.5 – 4.5	43	+1	-112	12	30
VCO-0964	951 - 977	1 – 4	13	+5	-112	12	15
VCO-1050	900 - 1200	1 – 8	60	+11	-100	12	28
VCO-1140	1070 - 1210	0.5 – 4.5	37	+1.5	-109	12	20
VCO-1525	1500 - 1550	0.3 – 4.7	25	+0.5	-110	12	30
VCO-1540	1435 - 1650	0.5 – 5	80	+7	-90	12	15
VCO-1700	1550 - 1850	0.25 – 4.75	85	+1.5	-99	12	15
VCO-1713	1683 - 1743	1.5 – 8	22	+5	-108	12	25
VCO-1720	1430 - 2010	2 – 14	68	+6	-98	12	18
VCO-2050	1950 - 2150	0.5 – 4.5	72	+5	-96	12	20
VCO-2100	2050 - 2150	0.5 – 4.5	36	+4	-106	12	27
VCO-2200	2150 - 2240	0.5 – 4.5	36	+4	-105	12	28
VCO-2265	2165 - 2360	0.5 – 10	56	+5	-99	12	25
VCO-2375	2300 - 2450	0.5 – 4.5	50	+3	-101	12	30
VCO-2800	2700 - 2900	0.5 – 4.5	75	+5	-95	12	18
VCO-2945	2900 - 2990	0.5 – 4.5	36	+1	-100	12	30
VCO-3000	2960 - 3030	0.5 – 4.5	33	+1	-105	12	30
VCO-3300	3200 - 3400	0.5 – 4.5	98	+5	-88	12	22
VCO-5320	5220 - 5420	0.5 – 4.5	108	-1	-83	12	15

Block Down Converter BDC Series

Part Number	RF Input Frequency (MHz)	RF Output Frequency (MHz)	Max Input Power (dBm)	Conversion Gain (dB)	SSB Phase Noise (dBc/Hz@10KHz)	Internal LO Freq (MHz)	DC Power (V/mA)
BDC-1800	1800 - 3600	DC - 1800	-5	-3 to +7	-93	1800	12/350
BDC-1950	1950 - 3900	DC - 1950	-5	-3 to +7	-93	1950	12/350
BDC-2400	2400 - 4800	DC - 2400	-5	-3 to +7	-92	2400	12/350
BDC-3200	3200 - 6400	DC - 3200	-7	-5 to +5	-80	3200	12/300

Bandpass Filter BPF Series

Part Number	Center Frequency (MHz)	Passband (MHz)	Insertion Loss (dB)	Rejection Frequency F_L (dB@MHz)	Rejection Frequency F_H (dB@MHz)	VSWR (In/Out)	Max Input (dBm)
BPF-45X	45	FO±5KHz	12.0	40@44.996	30@45.004	5.0/5.0	+20
BPF-70S	70	69.6 – 70.4	4.8	35@68.6	35@71.4	2.0/2.0	+30
BPF-75M	75	60 – 90	1.8	47@30	45@155	1.3/1.3	+20
BPF-103M	103	75 – 131	1.7	42@45	42@210	1.3/1.7	+27
BPF-140M	140	130 – 150	2.5	29@100	31@180	1.35/1.35	+24
BPF-204M	204	175 – 237	2.5	45@115	44@350	1.4/1.4	+27
BPF-253M	253	186 – 340	1.2	40@120	39@500	1.7/1.7	+27
BPF-280M	280	260 – 310	2.6	45@180	45@420	1.6/1.6	+27
BPF-315S	315	314 – 316	3.0	53@310	45@320	1.5/1.5	+10
BPF-325S	325	321.5 – 328.5	3.0	60@280	60@370	1.5/1.5	+20
BPF-650L	650	500 - 800	2.0	40@300	30@1000	2.0/2.0	+39
BPF-850L	850	700 - 1000	2.0	40@400	40@1500	2.0/2.0	+39
BPF-915C	915	902 - 928	1.5	45@800	40@1000	2.0/2.0	+33
BPF-915S	915	902 - 928	1.8	60@870	38@960	1.4/1.4	+15
BPF-935S	935	920 - 950	3.5	30@890	47@980	2.0/2.0	+20
BPF-950L	950	700 - 1200	2.0	57@200	42@2450	2.0/2.0	+39
BPF-1150L	1150	700 - 1600	2.0	57@200	40@2200	2.0/2.0	+39
BPF-1350L	1350	700 - 2000	2.0	60@100	44@2450	2.0/2.0	+39







Part Number	Center Frequency (MHz)	Passband (MHz)	Insertion Loss (dB)	Rejection Frequency F _L (dB@MHz)	Rejection Frequency F _H (dB@MHz)	VSWR (In/Out)	Max Input (dBm)
BPF-1575S	1575	1565 - 1585	1.8	45@1515	55@1635	1.1/1.1	+20
BPF-1960S	1960	1930 - 1990	1.8	30@1870	30@2050	1.8/1.8	+20
BPF-2600C	2600	2500 - 2700	1.8	53@2300	53@3000	2.3/2.3	+33

RF Power Detector RPD Series

Part Number	Input Frequency (MHz)	Dynamic Range (dB)	Output Voltage(V)	Output Slope	Response Time (μs)	VSWR (Input)	DC Power (V/mA)
RPD-5501	50 - 5000	30	0.1 - 5	Positive	7	1.4:1	5V/2mA
RPD-5513	30 - 4000	80	0.5 - 2	Positive	0.2	1.5:1	5V/30mA
RPD-5534	50 - 3000	60	0.1 - 2.5	Positive	0.3	1.3:1	5V/12mA

RF Switch RFS Series

Part Number	Frequency (MHz)	Insertion Loss (dB)	Isolation (dB)	Maximum Input Power (dBm)	Switching Time (μs)	VSWR	Control Voltage	DC Power (V/mA)
RFS-1	30 - 530	1.0	0.1 - 5	+37	0.15	1.2:1	0V/5V	5V/1mA
RFS-2	50 - 1500	1.0	0.1 - 5	+36	1.5	1.2:1	0V/5V	5V/1mA

LNA/LPA/LRA Series	ENA/EPA Series	GNA/GPA Series	RFS Series
			
MGA/MRA Series	MPA Series	HPA Series	SPA Series
			
DCA Series	FBS/FAS/FDS/FPS Series	FMR/FVR Series	FDR Series
			
QDR Series	MXR Series	GXR Series	PSC Series
			
DCR Series	PDF Series	PLO Series	BDC Series
			
TCXO Series	VCO Series	BPF Series	RPD Series
			