

2 系列可调衰减器

型号	频率范围 (GHz)	衰减步级	最大驻波比	插入损耗 (dB)	功率	衰减精度 (dB)
RBS-11-1-2 RBS-11-1-2-10W	DC-1	0-11dB in 0.1dB steps	1.25	≤0.6	2W 10W	±0.2dB(≤1dB) ±0.3dB (>1dB)
RBS-11-2.5-2 RBS-11-2.5-2-10W	DC-2.5		1.4	≤1.0	2W 10W	
RBS-11-3-2 RBS-11-3-2-10W	DC-3		1.4	≤1.2	2W 10W	
RBS-11-4.3-2 RBS-11-4.3-2-10W	DC-4.3		1.5	≤1.5	2W 10W	
RBS-11-6-2 RBS-11-6-2-10W	DC-6		1.5	≤1.5	2W 10W	
RBS-70-1-2 RBS-70-1-2-10W	DC-1	0-70dB in 1dB steps	1.25	≤0.6	2W 10W	±0.3dB(≤10dB) ±0.8dB(≤60dB) ±1.5dB(>60dB)
RBS-70-2.5-2 RBS-70-2.5-2-10W	DC-2.5		1.4	≤1.0	2W 10W	
RBS-70-3-2 RBS-70-3-2-10W	DC-3		1.4	≤1.2	2W 10W	
RBS-70-4.3-2 RBS-70-4.3-2-10W	DC-4.3		1.5	≤1.5	2W 10W	
RBS-70-6-2 RBS-70-6-2-10W	DC-6		1.5	≤1.5	2W 10W	
RBS-100-1-2 RBS-100-1-2-10W	DC-1	0-100dB in 1dB steps	1.25	≤0.6	2W 10W	±0.3dB(≤10dB) ±0.8dB(≤60dB) ±1.5dB(≤70dB) ±3.5% (>70dB)
RBS-100-2.5-2 RBS-100-2.5-2-10W	DC-2.5		1.4	≤1.0	2W 10W	
RBS-100-3-2 RBS-100-3-2-10W	DC-3		1.4	≤1.2	2W 10W	

连接器类型: SMA, N

尺寸: $\Phi 30 \times 120\text{mm}$ 