

7 系列可调衰减器

型号	功率	频率范围(GHz)	衰减步级	最大驻波比	插入损耗(dB)	衰减精度(dB)
RBS--69-8-7 RBS--69-8-7-10W	2W 10W	DC-8	0-69dB in 1dB steps	1.50	≤ 1.25	$\pm 0.5\text{dB}$ (0~9dB) $\pm 1.0\text{dB}$ (10~19dB) $\pm 1.5\text{dB}$ (20~70dB)
RBS--69-12.4-7 RBS--69-12.4-7-10W	2W 10W	DC-12.4		1.60	≤ 1.5	$\pm 0.8\text{dB}$ (0~9dB) $\pm 1.0\text{dB}$ (10~19dB) $\pm 1.5\text{dB}$ (20~70dB)
RBS--69-18-7 RBS--69-18-7-10W	2W 10W	DC-18		1.75	≤ 1.75	
RBS--69-26.5-7 RBS--69-26.5-7-10W	2W 10W	DC-26.5		1.85	≤ 2	
RBS--99-8-7 RBS--99-8-7-10W	2W 10W	DC-8	0-99dB in 1dB steps	1.50	≤ 1.25	$\pm 0.5\text{dB}$ (0~9dB) $\pm 1.0\text{dB}$ (10~19dB) $\pm 1.5\text{dB}$ (20~49dB) $\pm 2.0\text{dB}$ (50~69dB) $\pm 2.5\text{dB}$ (70~99dB)
RBS--99-12.4-7 RBS--99-12.4-7-10W	2W 10W	DC-12.4		1.60	≤ 1.5	$\pm 0.8\text{dB}$ (0~9dB) $\pm 1.0\text{dB}$ (10~19dB) $\pm 1.5\text{dB}$ (20~49dB) $\pm 2.0\text{dB}$ (50~69dB) $\pm 2.5\text{dB}$ (70~99dB)
RBS--99-18-7 RBS--99-18-7-10W	2W 10W	DC-18		1.75	≤ 1.75	

连接器类型: N, SMA, 3.5mm

尺寸: 137×102×82mm

